

9661-ETW

MTL intrinsically safe ethernet to serial
4 port communication module



DECLARATION OF CONFORMITY

A printed version of the Declaration of Conformity has been provided separately within the original shipment of goods. However, you can find a copy of the latest version at -

<http://www.mtl-inst.com/certificates>

CONTENTS

1	INTRODUCTION	1
2	FEATURES	1
3	CONNECTIONS	2
3.1	Data	2
3.2	Power.....	2
4	INSTALLATION	3
4.1	Special Conditions for Safe Use (Conditions of Certification)	3-4
5	CONNECTING THE 9661-ETW TO A PC/NETWORK	5
5.1	Connecting with LAN.....	5
6	CONFIGURING WI-FI NETWORK SETTINGS	6-7
7	SETTING UP THE 9661-ETW COMMS PORTS	8-9
7.1	LED Indication.....	9
8	MECHANICAL DETAILS	10
9	ENVIRONMENTAL	10
10	WASTE REMOVAL INFORMATION	10
11	CONFORMITY	10
12	MAINTENANCE	10
13	CERTIFICATION	11
13.1	Marking details	11
14	ORDERING INFORMATION	11

9661-ETW MTL Intrinsically Safe Ethernet to serial 4 port communication module



1 INTRODUCTION

The 9661-ETW is an Intrinsically Safe (IS) Ethernet to Serial 4 Port Communication Module suitable for Zone 0 mounting with a suitable Ex ia Power Supply.

The Module allows existing Intrinsically Safe equipment with an RS485/RS422 or RS232/TTL port to become Ethernet Enabled via either Wi-Fi (WLAN) or a Cat5/6 cable connection into an IS Ethernet Network (LAN). The unit has 4 serial ports, each one supporting either RS485/RS422 or RS232/TTL depending upon the configuration required. There are 2 RJ45 (LAN) ports that support 10/100 IS Ethernet connections - these allow 'daisy-chaining' of units together.

Power (12V DC) is supplied to the module either locally or using Power over Ethernet (PoEx) from the LAN port - This requires the PoEx output to be wired to the Supply Input terminals by the user.

The compact and cost effective design makes it the ideal choice for many applications such as **Petrochemical** - Process Monitoring, Legacy Systems and **Mining** - Underground Communication Links, Machine Monitoring and Legacy Systems.

Electrical connections are made via cage-clamp plug/socket terminals along with a dual RJ45 type connector for the Ethernet LAN ports. Twin SMA Style RF connectors allow one or two antenna to be connected as required.

2 FEATURES

- Intrinsically Safe ATEX / IECEx certification
- 4 Communication Ports - RS232/485/422 (2 & 4 Wire)
- Serial Modbus Protocol
- Bluetooth Dual Mode V2.1 +EDR and V4.0 (Future development option)
- Wi-Fi supporting 802.11 a/b/g/n standards (2.4 & 5 GHz)
- Micro Access Point (Future development option)
- Dual Port Switch 10/100Mb LAN (daisy-chain capability)
- LAN or Wi-Fi to Serial comms
- Wi-Fi, Bluetooth & LAN co-existence
- Modbus/TCP <-> Modbus/RTU (or ASCII) Protocol
- Compact design
- Certified for a variety of applications including Mining
- Zone 0 mounting
- Connection into Zone 0 Gas or Zone 20 Dust Hazardous Areas

3 CONNECTIONS

3.1 Data

Comms Ports 1 + 2

Pin	Function	Pin	Function
Port 1			
1	Port1 - TX+/A	2	Port1 - TX-/B
3	Port1 - RX+	4	Port1 - RX-
5	Port1 - TXD (RS232)	6	0V
7	Port1 - RXD (RS232)	8	0V
Port 2			
9	Port2 - TX+/A	10	Port2 - TX-/B
11	Port2 - RX+	12	Port2 - RX-
13	Port2 - TXD (RS232)	14	0V
15	Port2 - RXD (RS232)	16	0V

Comms Ports 3 + 4

Pin	Function	Pin	Function
Port 3			
1	Port3 - TX+/A	2	Port3 - TX-/B
3	Port3 - RX+	4	Port3 - RX-
5	Port3 - TXD (RS232)	6	0V
7	Port3 - RXD (RS232)	8	0V
Port 4			
9	Port4 - TX+/A	10	Port4 - TX-/B
11	Port4 - RX+	12	Port4 - RX-
13	Port4 - TXD (RS232)	14	0V
15	Port4 - RXD (RS232)	16	0V

LAN Port 1

Pin	Function
1	Tx +
2	Tx -
3	Rx +
4	Spare
5	Spare
6	Rx -
7	Spare
8	Spare

LAN Port 2

Pin	Function
1	Tx +
2	Tx -
3	Rx +
4	PoEx + 12V*
5	PoEx + 12V*
6	Rx -
7	PoEx 0V*
8	PoEx 0V*

WiFi Antenna Connectors (SMA)

SMA Coonector	Antenna
Front	Main (2.4 + 5GHz)
Rear	MIMO (2.4GHz)

3.2 Power

Pin	Function
1	PoEx + 12V
2	NC
3	PoEx 0V
4	Power +12V
5	NC
6	Power 0V

*PoEx (Pins 1+3) must be linked back into the Power connections (Pins 4+6) if used.

4 INSTALLATION

This Equipment must be installed, operated and maintained only by trained competent personnel and in accordance with all appropriate international, national and local standard codes of practice and site regulation for intrinsically safe apparatus and in accordance with the instructions contained here.


The 9600-ET Ethernet I/O module range is designed in accordance with general electrical safety standards e.g. IEC 60950 or similar.

The equipment should not be used in the vicinity of chemicals which are known to damage plastics unless protected by an additional suitable enclosure

The connected power supply must be Intrinsically Safe, having a $U_o=14.4V$ or less and suitable for the intended gas or dust group.

The nominal power requirements are 12V @ 150mA.

- Example wiring information for typical field devices is shown in the following diagram (also reproduced on the units side label)



4.1 Special conditions for safe use (Conditions of certification)

The following conditions relate to safe installation and/or use of the equipment, this is an extract from the certificate CML 16ATEX2131X.

- 14.1 When used with Group I gases and Group III dust, the modules shall each be mounted within an enclosure providing a degree of protection of at least IP54. This shall be in accordance with EN 60529, and the mounting arrangement shall not impair the existing creepage and clearance distances. The enclosure shall also comply with the appropriate requirements of Clauses 7 and 8 of EN 60079-0.
- 14.2 The RJ45 connectors do not meet the ingress protection rating of IP20, when they are not fitted with either a connector or blanking plug. For Group II, the RJ45 connectors must be fitted with either a plug or blanking plug or the module shall be mounted in an enclosure meeting IP20
- 14.3 When used in Group II, under certain extreme circumstances, the non-metallic parts incorporated in the enclosure of this equipment may generate an ignition-capable level of electrostatic charge. Therefore, the equipment shall not be installed in a location where the external conditions are conducive to the build-up of electrostatic charge on such surfaces. In addition, the equipment shall only be cleaned with a damp cloth.
- 14.4 The supply to the modules must be derived from a suitably certified, intrinsically safe supply having a $U_0=14.4V$ or less and suitable for the intended gas or dust group.
- 14.5 In the case of any connection to the RS232/TTL circuits, if the transmit 'TX' line within both the cable and the other certified equipment can be shown to be suitably segregated from the receive line, 'RX', then U_i can be specified as 12.5 V. If the segregation cannot be proved, then U_i for both TX and RX must be specified as 5.88 V (Note: Suitable segregation for upto 30V as specified in Table 5 EN 60079-11 is a minimum of 2mm creepage and clearance, 0.7mm through casting compound or under coating, or 0.5mm solid insulation with CTI ≥ 100).
- 14.6 The values of C_o and L_o shall apply when one of the two conditions below is given:
 - The total L_i of the external circuit (excluding the cable) is $< 1\%$ of the L_o value, or,
 - The total C_i of the external circuit (excluding the cable) is $< 1\%$ of the C_o value. The above parameters are reduced to 50% when both of the two conditions below are given:
 - The total L_i of the external circuit (excluding the cable) $> 1\%$ of the L_o , and
 - The total C_i of the external circuit (excluding the cable) $> 1\%$ of the C_o .

NOTE


The reduced capacitance of the external circuit (including cable) shall not be greater than 1 μF for IIB and 600 nF for IIC.

- 14.7 The equipment shall be capable of withstanding an electric strength test using a test voltage of 500 Vac applied between the circuit and earth for 60 s. Alternatively, a voltage of 20% higher may be applied for 1 s. There shall be no evidence of flashover or breakdown and the maximum current flowing shall not exceed 5 mA.


5 CONNECTING THE 9661-ETW TO A PC/NETWORK

5.1 Connecting with LAN

- Ensure that the 9661-ETW unit is powered by a suitable IS supply, such as the MTL 9492-PS. PoEx can be used to power the unit via LAN port 2 if required.
- The 9661-ETW should then be connected to an IS Ethernet Network/PC using a suitable CAT5/6 cable. Either LAN Port 1 or 2 can be used. The other LAN port can be used for daisy chaining units together. PoEx only available on port 2.
- Run the 9461-ET Finder.exe program which can be found on the MTL website, this will automatically search for and locate any 9661-ETW units connected to the network.



- Click on the device that you are looking to configure, then click the "configure IP settings" button and this will bring up the following screen.



- Manually type in the settings that you require and then enter the password "CSL". Click the apply button to send the settings to the 9661-ETW.
- Reboot the device by either powering down or by clicking the "reboot" button in the above screen.
- Once the 9661-ETW is up and running, navigate to the IP Address that has been programmed into the unit using a web browser and you will see the following screen.

EAT•N
9661-ETW 4 Port Serial Gateway

- Information
- Wi-Fi Information
- Diagnostics
- Wi-Fi Diagnostics
- Configuration
- Wi-Fi Configuration
- Contact

CONNECTION INFORMATION				
Comm Port	1	2	3	4
RS232/RTT	RS232	RS232	RS232	RS232
RS485 2W/RS422 4W	RS422 4W	RS422 4W	RS422 4W	RS422 4W
Baudrate	115200	115200	115200	115200
Parity	NONE	NONE	NONE	NONE
Packet Timeout (ms)	100	100	100	100
Byte Timeout (ms)	10	5	5	5
Port Delay (ms)	0	0	0	0
RTS ON Delay (ms)	2	0	0	0
RTS OFF Delay (ms)	2	0	0	0
Modbus Mode	RTU	RTU	RTU	RTU
Modbus Slave Min	1	11	21	31
Modbus Slave Max	10	20	30	40
Modbus Slave Offset	0	-10	-20	-30

SYSTEM INFORMATION	
Status	HEALTHY
Serial Number	16/000007
Hardware Revision	0001
Software Revision	1.03

- This page shows the current configuration of the 4 Comms ports.

6 CONFIGURING WI-FI NETWORK SETTINGS

- Click on the Wi-Fi Information menu option and you will see the screen below

EAT•N
9661-ETW 4 Port Serial Gateway

- Information
- Wi-Fi Information
- Diagnostics
- Wi-Fi Diagnostics
- Configuration
- Wi-Fi Configuration
- Contact

WI-FI INFORMATION	
APPLICATION BUILD	000N-W25R-SP_v1.0.0.3-0-g99c3d47
SERIAL NUMBER	23394599133294
MAC ADDRESS	D4-CA-06-7D-41-8F
HOST NAME	9661W01

WI-FI STATUS	
CONNECTED	ColNetwork (Channel 1) CONNECTED
DHCP	OFF
IP ADDRESS	192.168.8.212
SUBNET MASK	255.255.255.0
GATEWAY	192.168.0.1
PRIMARY DNS SERVER	8.8.8.8
SECONDARY DNS SERVER	8.8.4.4

This shows information about the Wi-Fi module and the current settings associated with it, including whether there is an active Wi-Fi connection.

To change any of the settings this is done in the following step

- **Click on the Wi-Fi Configuration menu option**, this prompts the user to enter a username and password. The defaults are shown below, both are case sensitive –

Username: **admin**

Password: **Pa55w0rd**

You will then see the following screen

EAT•N
9661-ETW 4 Port Serial Gateway

Information
 Wi-Fi Information
 Diagnostics
 Wi-Fi Diagnostics
 Configuration
 Wi-Fi Configuration
 Contact

WIRELESS CONFIGURATION

SSID	CSLNetwork
AUTHENTICATION	WPA/WPA2 PSK
PASSWORD	*****
HOSTNAME	9661WiFi

WIRELESS NETWORK CONFIGURATION

DHCP	OFF
IP ADDRESS	192.168.0.212
SUBNET MASK	255.255.255.0
GATEWAY	192.168.0.1
PRIMARY DNS	8.8.8.8
SECONDARY DNS	8.8.4.4

- **SSID** – This should be configured to the same **SSID** as your access point / router you want the unit to connect to.
- **Authentication** – This enables **WPA/WPA2-PSK** security on the Wi-Fi link and is the recommended setting. The only other option is **Open** where no security is used.
- **Password** – This must match the password set on the access point / router you are trying to connect to
- **Hostname** – You can type any name you chose to help identify this device on your network
- There is also the option to use **DHCP** or use **fixed IP** address as required
- Click on the Wi-Fi Diagnostics menu option and you will see the screen below

EAT•N
9661-ETW 4 Port Serial Gateway

Information
 Wi-Fi Information
 Diagnostics
 Wi-Fi Diagnostics
 Configuration
 Wi-Fi Configuration
 Contact

[Click here to clear diagnostic counters](#)

Wi-Fi DIAGNOSTIC COUNTERS							
IP ADDRESS	IP PORT	TX PACKETS	RX PACKETS	BROADCASTS	EXCEPTIONS	PACKETS/S	MAX PKT/SEC
192.168.0.212	17003	37	37	0	0	0	400

- This page is similar to the Diagnostics page which shows information regarding the LAN and Serial Ports in that it provides information on the Wi-Fi connected Modbus/TCP clients and can be useful for fault finding.

7 SETTING UP THE 9661-ETW COMMS PORTS

To change any of the settings this is done in the following step

- Click on the **Wi-Fi Configuration menu option**, this prompts the user to enter a username and password. The defaults are shown below, both are case sensitive –

Username: **admin**

Password: **Pa55w0rd**

You will then see the following screen


- Click on the configuration menu option and you will see the screen below

- Using this page you can modify the current settings on each of the 4 Comms ports and set them up accordingly.
- The Slave offset allows the user the option of having the same serial slave addressed devices on the 4 ports. It uses the sign and offset value to alter the slave address received on the Ethernet before it is passed to the serial port. In the above screen, the following configuration is used;

Port	TCP Slave Address	Offset	Serial Slave Address
1	1-10	+0	1-10
2	11-20	-10	1-10
3	21-30	-20	1-10
4	31-40	-30	1-10

- The Modbus slave Min and Max sets the TCP slave address limits for that port.
- Packet Timeout sets the maximum time waiting for the first byte of a reply from a slave. (100ms is typical but may be extended for "slow" slaves or reduced for "fast" ones)

- Byte Timeout determines the end of a slaves reply as when another byte is not received during this time. (typically set between 2ms and 20ms depending upon Baudrate)
- Poll Delay slows down the packet rate if required. (Default is 0ms)
- RTS ON Delay gives a delay after RTS before the packet data is sent, RTS OFF gives a delay after the packet data is sent before releasing RTS signal (typically 0ms to 5ms)
- Once the settings have been configured, click the submit button. A confirmation message will be displayed for 3 seconds before returning back to the main page.
- Click on the Diagnostics page option and it will display the following screen.



- This page shows the counters for all of the LAN connected Modbus/TCP clients as well as the serial ports, this can be useful for fault finding

7.1 LED Indication

- The Following table shows the status of the LED's on the front of the 9661-ETW Module.

	OFF	FLASH	ON
PWR (green)	Power Fail	N/A	Power OK
WDG (red/green)	Fault	Green - Healthy (10Hz)	Fault
WLAN (red/blue)	Idle	Red (config mode) Blue (data)	Red (fault) Blue (connected) Purple (connecting)
TX (green)	Idle	Transmitting Serial Data	N/A
RX (red)	Idle	Receiving Serial Data	Fault – RX data polarity is inverted
STAT (red/green)	N/A	Green – Identify module mode	Red (fault) Green (healthy)
RJ45 ACT (yellow)	Ethernet link disconnected	Ethernet link activity	Ethernet link connected
RJ45 100 (green)	10Mbps	N/A	100Mbps

8 MECHANICAL DETAILS

Enclosure dimensions

Width	Height	Depth	Weight
45mm	147mm	155mm	357g

All values are approximate.

Mounting

- The 9661-ETW module will clip onto standard DIN Rail (TS35)
- Black plastic clips from the top and bottom of the module can be pulled out to allow it to sit over the DIN Rail, the clips will then be pushed back into place to secure the module.

9 ENVIRONMENTAL

Operating Temperature	-40°C...+70°C
Storage Temperature	-40°C...+70°C
Humidity	0...95% RH, non-condensing
Ingress Protection	Select enclosure to suit application, see certificates for information.

10 WASTE REMOVAL INFORMATION



The Electronic equipment within must not be treated as general waste. By ensuring that this product is disposed of correctly, you will be helping to prevent potentially negative consequences for the environment and human health, which could otherwise be caused by incorrect waste handling of this product.

For more detailed information about take-back and equipment recycling please contact your local Eaton MTL representative.

11 CONFORMITY

Refer To 9600 Series Declaration of Conformity

12 MAINTENANCE

There is no routine maintenance required


13 CERTIFICATION

Ex ia I Ma
Ex ia IIC T4 Ga
[Ex ia Da] IIIC T135°C

CML 16ATEX2131X
IECEX CML 16.0053X

See Certificates for further information

13.1 Marking details



Part No.	9661-ETW	4-Port Serial Gateway with WiFi
Part No.	9661-ET	4-Port Serial Gateway

14 ORDERING INFORMATION

- 9661-ETW 4-Port Serial Gateway with WiFi
- 9661-ET 4-Port Serial Gateway *

***Note:** 9661-ET may be subject to minimum order quantity.
Standard product is 9661-ETW (with WiFi)

AUSTRALIA

MTL Instruments Pty Ltd,
10 Kent Road, Mascot, New South Wales, 2020, Australia
Tel: +61 1300 308 374 Fax: +61 1300 308 463
E-mail: mtl-sales@eaton.com

BeNeLux

MTL Instruments BV
Ambacht 6, 5301 KW Zaltbommel
The Netherlands
Tel: +31 (0)418 570290 Fax: +31 (0)418 541044
E-mail: mtl.benelux@eaton.com

CHINA

Cooper Electric (Shanghai) Co. Ltd
955 Shengli Road, Heqing Industrial Park
Pudong New Area, Shanghai 201201
Tel: +86 21 2899 3817 Fax: +86 21 2899 3992
E-mail: mtl-cn@eaton.com

FRANCE

MTL Instruments srl,
7 rue des Rosieristes, 69410 Champagne au Mont d'Or
France
Tel: +33 (0)4 37 46 16 53 Fax: +33 (0)4 37 46 17 20
E-mail: mtlfrance@eaton.com

GERMANY

MTL Instruments GmbH,
Heinrich-Hertz-Str. 12, 50170 Kerpen, Germany
Tel: +49 (0)22 73 98 12 - 0 Fax: +49 (0)22 73 98 12 - 2 00
E-mail: csckkerpen@eaton.com

INDIA

MTL India,
No.36, Nehru Street, Off Old Mahabalipuram Road
Sholinganallur, Chennai - 600 119, India
Tel: +91 (0) 44 24501660 /24501857 Fax: +91 (0) 44 24501463
E-mail: mtlindiasales@eaton.com

ITALY

MTL Italia srl,
Via San Bovio, 3, 20090 Segrate, Milano, Italy
Tel: +39 02 959501 Fax: +39 02 95950759
E-mail: chmninfo@eaton.com

JAPAN

Cooper Crouse-Hinds Japan KK,
MT Building 3F, 2-7-5 Shiba Daimon, Minato-ku,
Tokyo, Japan 105-0012
Tel: +81 (0)3 6430 3128 Fax: +81 (0)3 6430 3129
E-mail: mtl-jp@eaton.com

NORWAY

Norex AS
Fekjan 7c, Postboks 147,
N-1378 Nesbru, Norway
Tel: +47 66 77 43 80 Fax: +47 66 84 55 33
E-mail: info@norex.no

RUSSIA

Cooper Industries Russia LLC
Elektrozavodskaya Str 33
Building 4
Moscow 107076, Russia
Tel: +7 (495) 981 3770 Fax: +7 (495) 981 3771
E-mail: mtlrussia@eaton.com

SINGAPORE

Eaton Industries Pte Ltd
100G Pasir Panjang Road, Interlocal Centre
#07-08 Singapore 118523
Tel: +65 6645 9888 Fax: +65 6297 4819
E-mail: sales.mtlsing@eaton.com

SOUTH KOREA

Cooper Crouse-Hinds Korea
7F. Parkland Building 237-11 Nonhyun-dong Gangnam-gu,
Seoul 135-546, South Korea.
Tel: +82 6380 4805 Fax: +82 6380 4839
E-mail: mtl-korea@eaton.com

UNITED ARAB EMIRATES

Cooper Industries/Eaton Corporation
Office 205/206, 2nd Floor SJ Towers, off. Old Airport Road,
Abu Dhabi, United Arab Emirates
Tel: +971 2 44 66 840 Fax: +971 2 44 66 841
E-mail: mtlgulf@eaton.com

UNITED KINGDOM

Eaton Electric Ltd,
Great Marlings, Butterfield, Luton
Beds LU2 8DL
Tel: +44 (0)1582 723633 Fax: +44 (0)1582 422283
E-mail: mtl-enquiry@eaton.com

AMERICAS

Cooper Crouse-Hinds MTL Inc.
3413 N. Sam Houston Parkway W.
Suite 200, Houston TX 77086, USA
Tel: +1 281-571-8065 Fax: +1 281-571-8069
E-mail: mtl-us-info@eaton.com