

1 **UK-TYPE EXAMINATION CERTIFICATE**

2 **Safety Device, Controlling Device or Regulating Device intended for use outside a potentially explosive atmosphere but required for or contributing to the safe functioning of Product and Protective Systems with respect to the risks of explosion**  
**UKSI 2016:1107 (as amended) – Schedule 3A, Part 1**

3 UK-Type Examination Certificate Number: **BAS21UKEX0553**

4 Product: **MTL4541S, MTL4541T, MTL4544S & MTL4544D Repeater Power Supplies, 4/20mA**

5 Manufacturer: **Eaton Electric Limited**

6 Address: **Great Marlings, Butterfield, Luton, Bedfordshire, LU2 8DL**

7 This product and any acceptable variation thereto is specified in the schedule to this certificate and the documents therein referred to.

8 SGS Baseefa, Approved Body number 1180, in accordance with Regulation 43 of the Equipment and Protective Systems Intended for Use in Potentially Explosive Atmospheres Regulations 2016, UKSI 2016:1107 (as amended), certifies that this product has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of products intended for use in potentially explosive atmospheres given in Schedule 1 of the Regulations.

The examination and test results are recorded in confidential Report No. **21(C)0386/30**

9 Compliance with the Essential Health and Safety Requirements has been assured by compliance with:  
**EN IEC 60079-0:2018 EN 60079-11:2012**

except in respect of those requirements listed at item 18 of the Schedule.

10 If the sign “X” is placed after the certificate number, it indicates that the product is subject to the Specific Conditions of Use specified in the schedule to this certificate.

11 This UK-TYPE EXAMINATION CERTIFICATE relates only to the design and construction of the specified product. Further requirements of the Regulations apply to the manufacturing process and supply of this product. These are not covered by this certificate.

12 The marking of the product shall include the following:

⊕ II (1) GD [Ex ia Ga] IIC (-20°C ≤ Ta ≤ +60°C)  
[Ex ia Da] IIIC (-20°C ≤ Ta ≤ +60°C)

⊕ I (M1) [Ex ia Ma] I (-20°C ≤ Ta ≤ +60°C)

SGS Baseefa Customer Reference No. **0703**


Project File No. **21/0386**

This document is issued by the Company subject to its General Conditions for Certification Services accessible at <http://www.sgs.com/en/Terms-and-Conditions.aspx> and the Supplementary Terms and Conditions accessible at <http://www.sgs.com/SGSBaseefa/Terms-and-Conditions.aspx>. Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained herein reflects the Company’s findings at the time of its intervention only and within the limits of Client’s instructions, if any. It does not necessarily indicate that the equipment may be used in particular industries or circumstances. The Company’s sole responsibility is to its Client and this document does not exonerate parties to a transaction from exercising all their rights and obligations under the transaction documents. This document cannot be reproduced except in full, schedule included, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.

**SGS Baseefa Limited**

Rockhead Business Park, Staden Lane,  
Buxton, Derbyshire SK17 9RZ  
Telephone +44 (0) 1298 766600 Fax +44 (0) 1298 766601  
e-mail [baseefa@sgs.com](mailto:baseefa@sgs.com) web site  
[www.sgs.co.uk/sgsbaseefa](http://www.sgs.co.uk/sgsbaseefa)  
Registered in England No. 4305578.  
Registered address: Rossmore Business Park, Ellesmere Port, Cheshire,  
CH65 3EN



  
R S SINCLAIR  
TECHNICAL MANAGER  
On behalf of SGS Baseefa Limited

13

## Schedule

14

### Certificate Number BAS21UKEX0553

#### 15 Description of Product

The MTL4544S Two Channel Repeater Power Supply, 4/20mA for 'Smart' Transmitters is designed to provide floating d.c. supplies for energising two 'Smart' 4/20mA Transmitters located in the hazardous area and repeat these currents in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC).

The MTL4544S Two Channel Repeater Power Supply, 4/20mA for 'Smart' Transmitters comprises four isolating transformers that provide galvanic isolation between the hazardous and non-hazardous area circuitry, zener diode chains and resistors providing voltage and current limitation. The above, together with other electronic components are mounted on a single printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plugs and sockets are provided for hazardous and non-hazardous area connections. LED indication is fitted to indicate power-on.

The MTL4541S Single Channel Repeater Power Supply, 4/20mA for 'Smart' Transmitters is a depopulated version of the MTL4544S and has only one channel populated.

The MTL4544D Repeater Power Supply, 4/20mA for 2 or 3 Wire Transmitters with two outputs is designed to provide a floating d.c. supplies for energising a 2 or 3-Wire 4/20mA Transmitter located in the hazardous area and repeat the current on two channels in the non-hazardous area, whilst restricting the transfer of energy from the unspecified non-hazardous area apparatus to the intrinsically safe circuits by means of limitation of current and voltage. The apparatus also allows bi-directional signal communication between the hazardous and non-hazardous area by the connection of a hand-held communicator (HHC). The apparatus uses the same printed circuit board and enclosure as the MTL4544S but is populated with only one hazardous area transmitter connection and two non-hazardous area outputs fitted.

The MTL4541T Single Channel Repeater Power Supply, 4/20mA for 2 or 3-Wire Transmitters is similar to the MTL4541S but is fitted with different voltage and current limitation components and therefore has different output parameters.

#### MTL4541S, MTL4544S & MTL4544D Input / Output Parameters

##### Non-hazardous Area Terminals 8, 9, 11, 12, 13 & 14

$$U_m = 253V \text{ r.m.s.}$$

The apparatus is designed to operate on non-hazardous area terminals 8, 9, 11, 12, 13 & 14 from a d.c. supply voltage of up to 35V.

##### Hazardous Area Terminals 2 w.r.t. 1 (Channel 1)

Or

##### Hazardous Area Terminals 5 w.r.t. 4 (Channel 2 – MTL4544S model)

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 93mA & L_i = 0 \\ P_o = 0.65W & \end{array}$$

##### Hazardous Area Terminals 3 w.r.t. 1 (Channel 1)

Or

##### Hazardous Area Terminals 6 w.r.t. 4 (Channel 2 – MTL4544S model)

$$\begin{array}{llll} U_o = 1.1V & U_i = 30V & C_i = 0 \\ I_o = 53mA & I_i = 121mA & L_i = 0 \\ P_o = 15mW & \end{array}$$

Although the apparatus does not comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when terminals 3 w.r.t. 1 or terminals 6 w.r.t 4 (MTL4544S model only) are connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

When an external intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source. Hazardous area terminals 2 and 5 must not be used when the source is connected.

Hazardous Area Terminals 2 w.r.t. 3 (Channel 1)

Or

Hazardous Area Terminals 5 w.r.t. 6 (Channel 2 – MTL4544S model)

$$\begin{array}{ll} U_o = 28V & C_i = 0 \\ I_o = 87mA & L_i = 0 \\ P_o = 0.61W & \end{array}$$

Each channel must be considered as a separate intrinsically safe circuit.

Load Parameters

The capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values for either channel:

| GROUP   | CAPACITANCE<br>( $\mu$ F) | INDUCTANCE<br>(mH) | OR | L/R RATIO<br>( $\mu$ H/ohm) |
|---|---------------------------|--------------------|----|-----------------------------|
| Hazardous Area Terminals 2 w.r.t. 1 or 5 w.r.t. 4 (MTL4544S only) |                           |                    |    |                             |
| IIC   | 0.083                     | 4.2                |    | 56                          |
| IIB*  | 0.65                      | 12.6               |    | 210                         |
| IIA   | 2.15                      | 33.6               |    | 444                         |
| I   | 3.76                      | 53.7               |    | 668                         |
| Hazardous Area Terminals 3 w.r.t. 1 or 6 w.r.t 4 (MTL4544S only)  |                           |                    |    |                             |
| IIC   | 100                       | 12.8               |    | 2,438                       |
| IIB*  | 1,000                     | 47.8               |    | 8,932                       |
| IIA   | 1,000                     | 104.7              |    | 18,140                      |
| I   | 1,000                     | 156.2              |    | 28,229                      |
| Hazardous Area Terminals 2 w.r.t. 3 or 5 w.r.t. 6 (MTL4544S only) |                           |                    |    |                             |
| IIC   | 0.083                     | 4.9                |    | 59                          |
| IIB*  | 0.65                      | 20.0               |    | 222                         |
| IIA   | 2.15                      | 40.9               |    | 469                         |
| I   | 3.76                      | 59.1               |    | 710                         |

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is  $< 1\%$  of the  $C_o$  value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq 1\%$  of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than  $1\mu$ F for Groups IIB, IIA & I and  $600n$ F for Group IIC.

**MTL4541T Input / Output Parameters**

**Non-hazardous Area Terminals 8, 9, 11, 13 & 14**

$$U_m = 253V \text{ r.m.s.}$$

The apparatus is designed to operate on non-hazardous area terminals 8, 9, 11, 13 & 14 from a d.c. supply voltage of up to 35V.

**Hazardous Area Terminals 2 w.r.t. 1**

$$\begin{array}{ll} U_o = 22V & C_i = 0 \\ I_o = 167mA & L_i = 0 \\ P_o = 0.92W & \end{array}$$

**Hazardous Area Terminals 3 w.r.t. 1**

$$\begin{array}{llll} U_o = 1.0V & U_i = 30V & C_i = 0 \\ I_o = 53mA & I_i = 121mA & L_i = 0 \\ P_o = 14mW & \end{array}$$

Although the apparatus does not comply with the simple apparatus requirements of Clause 5.7 of EN 60079-11: 2012, when terminals 3 w.r.t. 1 are connected in an intrinsically safe circuit the internal stored energy, voltage and current of the interface will not add more than the values specified in Clause 5.7 of EN 60079-11: 2012 to the parameters of the circuit into which it is connected.

When an external intrinsically safe source is connected to these terminals it should have a source resistance of  $U_i / I_i$  and the capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area connections must not exceed the values detailed in the certificate of the intrinsically safe source. Hazardous area terminal 2 must not be used when the source is connected.

**Hazardous Area Terminals 2 w.r.t. 3**

$$\begin{array}{ll} U_o = 22V & C_i = 0 \\ I_o = 145mA & L_i = 0 \\ P_o = 0.80W & \end{array}$$

**Load Parameters**

The capacitance and either the inductance or inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

| GROUP                                      | CAPACITANCE<br>( $\mu$ F) | INDUCTANCE<br>(mH) | OR | L/R RATIO<br>( $\mu$ H/ohm) |
|--|---------------------------|--------------------|----|-----------------------------|
| <b>Hazardous Area Terminals 2 w.r.t. 1</b> |                           |                    |    |                             |
| IIC  | 0.165                     | 0.91               |    | 39                          |
| IIB*                                       | 1.14                      | 5.5                |    | 147                         |
| IIA  | 4.20                      | 10.7               |    | 322                         |
| I  | 6.00                      | 16.4               |    | 517                         |
| <b>Hazardous Area Terminals 3 w.r.t. 1</b> |                           |                    |    |                             |
| IIC  | 100                       | 12.8               |    | 2,438                       |
| IIB*                                       | 1,000                     | 47.8               |    | 8,932                       |
| IIA  | 1,000                     | 104.7              |    | 18,140                      |
| I  | 1,000                     | 156.2              |    | 28,229                      |

| GROUP                               | CAPACITANCE<br>( $\mu$ F) | INDUCTANCE<br>(mH) | OR | L/R RATIO<br>( $\mu$ H/ohm) |
|-------------------------------------|---------------------------|--------------------|----|-----------------------------|
| Hazardous Area Terminals 2 w.r.t. 3 |                           |                    |    |                             |
| IIC                                 | 0.165                     | 1.49               |    | 45                          |
| IIB*                                | 1.14                      | 7.5                |    | 174                         |
| IIA                                 | 4.20                      | 14.9               |    | 381                         |
| I                                   | 6.00                      | 22.5               |    | 575                         |

\* Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- The above load parameters apply when one of the two conditions below is given:
  - the total  $L_i$  of the external circuit (excluding the cable) is < 1% of the  $L_o$  value or
  - the total  $C_i$  of the external circuit (excluding the cable) is < 1% of the  $C_o$  value.
- The above parameters are reduced to 50% when both of the two conditions below are given:
  - the total  $L_i$  of the external circuit (excluding the cable) is  $\geq$  1% of the  $L_o$  value and
  - the total  $C_i$  of the external circuit (excluding the cable) is  $\geq$  1% of the  $C_o$  value.

The reduced capacitance of the external circuit (including cable) shall not be greater than 1 $\mu$ F for Groups IIB, IIA & I and 600nF for Group IIC.

**16 Report Number**

21(C)0386/30

**17 Specific Conditions of Use**

None

**18 Essential Health and Safety Requirements**

In addition to the Essential Health and Safety Requirements (EHSRs) covered by the standards listed at item 9, the following are considered relevant to this product:

| Clause | Subject  | Compliance                    |
|--------|--|-------------------------------|
| 13     | Protection against other hazards (LVD type requirements, etc.) | Manufacturer responsibility   |
| 14     | Overloading of equipment (protection relays, etc.)             | User/Installer responsibility |
| 22(1)  | External effects   | User/Installer responsibility |
| 22(2)  | Aggressive substances, etc.                                    | User/Installer responsibility |

**19 Drawings and Documents**

| Number   | Sheet  | Issue | Date | Description  |
|----------|--------|-------|------|--|
| CI4541-3 | 8 of 8 | 5     | 8.21 | MTL4541S, MTL4541T, MTL4544S, MTL4544D,<br>Certification Label Details - Baseefa |

For other current drawings not re-submitted for this assessment see Baseefa09ATEX0155.