



IECEX Certificate of Conformity

INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification System for Explosive Atmospheres

for rules and details of the IECEx Scheme visit www.iecex.com

Certificate No.:	IECEX BAS 12.0003X	Page 1 of 4	<u>Certificate history:</u>
Status:	Current	Issue No: 4	Issue 3 (2016-09-20)
Date of Issue:	2021-08-12		Issue 2 (2015-05-14)
Applicant:	Eaton Electric Limited Great Marlings Butterfield Luton Bedfordshire LU2 8DL United Kingdom		Issue 1 (2014-05-19)
Equipment:	SD**xxx Series Surge Protection Devices		Issue 0 (2012-01-20)
Optional accessory:			
Type of Protection:	Intrinsic Safety		
Marking:	Ex ia IIC T4 Ga (-30°C ≤ Ta ≤ See Annex)		

Approved for issue on behalf of the IECEx
Certification Body:

R S Sinclair

Position:

Technical Manager

Signature:
(for printed version)

Date:

13/8/2021

1. This certificate and schedule may only be reproduced in full.
2. This certificate is not transferable and remains the property of the issuing body.
3. The Status and authenticity of this certificate may be verified by visiting www.iecex.com or use of this QR Code.



Certificate issued by:

SGS Baseefa Limited
Rockhead Business Park
Staden Lane
Buxton, Derbyshire, SK17 9RZ
United Kingdom





IECEX Certificate of Conformity

Certificate No.: **IECEX BAS 12.0003X**

Page 2 of 4

Date of issue: 2021-08-12

Issue No: 4

Manufacturer: **Eaton Electric Limited**
Great Marlings
Butterfield
Luton
Bedfordshire
LU2 8DL
United Kingdom

Additional manufacturing locations: **MTL Instruments PVT Limited**
No 3 Old Mahabalipuram Road
Sholinganallur
Chennai
600 119
India

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEX Quality system requirements. This certificate is granted subject to the conditions as set out in IECEX Scheme Rules, IECEX 02 and Operational Documents as amended

STANDARDS :

The equipment and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards

IEC 60079-0:2017 Explosive atmospheres - Part 0: Equipment - General requirements
Edition:7.0

IEC 60079-11:2011 Explosive atmospheres - Part 11: Equipment protection by intrinsic safety "i"
Edition:6.0

This Certificate **does not** indicate compliance with safety and performance requirements other than those expressly included in the Standards listed above.

TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in:

Test Reports:

[GB/BAS/ExTR12.0007/00](#)
[GB/BAS/ExTR16.0245/00](#)

[GB/BAS/ExTR13.0295/00](#)
[GB/BAS/ExTR21.0130/00](#)

[GB/BAS/ExTR15.0096/00](#)

Quality Assessment Reports:

[GB/BAS/QAR06.0022/08](#)

[GB/BAS/QAR07.0017/09](#)



IECEX Certificate of Conformity

Certificate No.: **IECEX BAS 12.0003X**

Page 3 of 4

Date of issue: 2021-08-12

Issue No: 4

EQUIPMENT:

Equipment and systems covered by this Certificate are as follows:

The range designated as the SD**xxx Series Surge Protection Devices are designed to protect instrumentation and electronic systems from surges and transients conducted through signal cables. The apparatus comprises a printed circuit board (p.c.b.) upon which are mounted all of the electrical components. The units use two and three terminal gas discharge tubes, diodes, zener diodes, resistors and inductors for operational purposes and may be optionally encapsulated. The p.c.b. is housed within a plastic enclosure with two groups of three terminals (1, 2 & 3 and 4, 5 & 6) at either end of the enclosure, for the connection of the interconnecting cables. An earth shoe is fitted to the apparatus to enable connection of an earth bonding conductor with a cross sectional area of at least 4mm². The SD**xxx Series comprises:- SD**X (two wire and earth with Li = 0.22mH) and SD**T3 (three wire and earth with Li = 0.22mH). The apparatus in each of these series, differ only in the operating voltage. The “***” in the apparatus title indicates the nominal voltage the apparatus is designed to work at. For example a unit marked SD07R has a nominal working voltage of 7V and an operating voltage of 7.5V. The working voltage and operating voltage of the devices are not critical for the safety assessment. Three further units are included the SD**R, SD**R3 and SDrtD.

The range designated as the SD**Mxxx Series Surge Protection Devices are designed to protect instrumentation and electronic systems from surges and transients conducted through signal cables. The SD**Mxxx Series Surge Protection Devices are based on a module construction and comprise a ‘module base’ unit which has four options and a plug in surge ‘module insert’ which has thirty two options. Once the ‘module insert’ is installed into the ‘module base’ unit it is retained in place by a locking bar.

The SD**xxx Series Surge Protection Devices and SD**Mxxx Series Surge Protection Devices may be located in a hazardous area.

For the full details of the units covered, the Input and output parameters and the Ambient Temperature limits, see the Annex.

SPECIFIC CONDITIONS OF USE: YES as shown below:

1. The plastic enclosure may present an electrostatic risk and must be cleaned only with a damp cloth.
2. The range of SD**xxx Series Surge Protection Devices and SD**Mxxx Series Surge Protection Devices will not meet the 500V insulation requirements to earth, therefore suitable precautions must be taken when installing the apparatus.



IECEX Certificate of Conformity

Certificate No.: **IECEX BAS 12.0003X**

Page 4 of 4

Date of issue: 2021-08-12

Issue No: 4

DETAILS OF CERTIFICATE CHANGES (for issues 1 and above) Variation 4.1

This issue of the certificate permits the additional labelling method of laser etching and confirms the current design meets the requirements of IEC 60079-0:2017.

ExTR: GB/BAS/ExTR21.0130/00	File Reference: 21/0398
------------------------------------	--------------------------------

Annex:

[IECEX BAS 12.0003X - Annex - Issue 2.pdf](#)

The SD**xxx Series Surge Protection Devices are designed to protect instrumentation and electronic systems from surges and transients conducted through signal cables.

The apparatus comprises a printed circuit board (PCB) upon which are mounted all of the electrical components. The units use two and three terminal gas discharge tubes, diodes, zener diodes, resistors and inductors for operational purposes and may be optionally encapsulated. The PCB is housed within a plastic enclosure with two groups of three terminals (1, 2 & 3 and 4, 5 & 6) at either end of the enclosure, for the connection of the interconnecting cables. An earth shoe is fitted to the apparatus to enable connection of an earth bonding conductor with a cross sectional area of at least 4mm².

The SD**xxx Series comprises:- SD**X (two wire and earth with $L_i = 0.22\text{mH}$) and SD**T3 (three wire and earth with $L_i = 0.22\text{mH}$). The apparatus in each of these Series, differ only in the operating voltage. The “***” in the apparatus title indicates the nominal voltage the apparatus is designed to work at. For example a unit marked SD07R has a nominal working voltage of 7V and an operating voltage of 7.5V. The working voltage and operating voltage of the devices are not critical for the safety assessment.

The SD**xxx Series Surge Protection Devices may be located in a hazardous area. For all units the permitted input current reduces as the voltage increases and the different input power limit determines the upper limit on the permitted ambient temperature range. The Surge Protected Devices are passive and therefore the surge protected output parameters are equal to the parameters of the device connected to the field terminals.

The parameters for all of the SD**X and SD**T3 units are:-

All SD**X and SD**T3 units are marked Ex ia IIC T4 Ga ($-30^\circ\text{C} \leq T_a \leq \text{See below}$)

Input : Field Terminals

$$U_i = 20\text{V} \quad I_i = 260\text{mA}$$

or $U_i = 26\text{V} \quad I_i = 175\text{mA}$

or $U_i = 28\text{V} \quad I_i = 140\text{mA}$

or $U_i = 60\text{V} \quad I_i = 65\text{mA}$

$$P_i = 1\text{W} \quad (-30^\circ\text{C} \leq T_a \leq 75^\circ\text{C})$$

or $P_i = 1.2\text{W} \quad (-30^\circ\text{C} \leq T_a \leq 60^\circ\text{C})$

or $P_i = 1.3\text{W} \quad (-30^\circ\text{C} \leq T_a \leq 40^\circ\text{C})$

$$C_i = 0$$

$$L_i = 0.22\text{mH}$$

Output : Surge Protected Terminals

$$U_o \leq U_i$$

$$I_o \leq I_i$$

$$P_o \leq P_i$$

The surge protected output parameters are equal to the parameters of the device connected to the field terminals.

Variation 0.1

To permit the removal of the inductors and other changes which do not affect the intrinsic safety assessment thus forming the SD**R (two wire and earth with $L_i = 0$) and SD**R3 and SDrtd. (three wire and earth with $L_i = 0$). The SDrtd unit differs from the SD**R3, due to the use of matched resistors in the three signal lines. The apparatus in each of the series differ only in the operating voltage. The “***” in the apparatus title indicates the nominal voltage the apparatus is designed to work at. The nominal working voltage and operating voltage of the devices are not critical for the safety assessment.

The parameters for all of the SD**R, SD**R3 and SDrt. units are:-

All the SD**R, SD**R3 and SDrt. units are marked Ex ia IIC T4 Ga (-30°C ≤ Ta ≤ See Below)

Input : Field Terminals

$$U_i = 60V$$

$$I_i = 260mA$$

$$P_i = 1W \quad (-30^\circ C \leq T_a \leq 75^\circ C)$$

or $P_i = 1.2W \quad (-30^\circ C \leq T_a \leq 60^\circ C)$

or $P_i = 1.3W \quad (-30^\circ C \leq T_a \leq 40^\circ C)$

$$C_i = 0$$

$$L_i = 0$$

Output : Surge Protected Terminals

$$U_o \leq U_i$$

$$I_o \leq I_i$$

$$P_o \leq P_i$$

The surge protected output parameters are equal to the parameters of the device connected to the field terminals.

Variation 0.2

To permit the introduction of an extension to the range of SD**xxx Surge Protection Devices which are designated as the SD**Mxxx Series Surge Protection Devices which are designed to protect instrumentation and electronic systems from surges and transients conducted through signal cables.

The SD**Mxxx Series Surge Protection Devices are based on a module construction and comprise a 'module base' unit which has four options and a plug in surge 'module insert' which has thirty options. Once the 'module insert' is installed into the 'module base' unit it is retained in place by a locking bar.

The 'module base' unit comprises three input terminals, three output terminals and a printed circuit board, all mounted in an enclosure provided with a mounting slot for the 'module insert' and a conductive foot for mounting on a standard DIN rail. With the exception of the mounting foot this enclosure provides a degree of protection of at least IP20 for the electrical circuit irrespective of whether the 'module insert' is fitted. A gas discharge tube may be inserted in the connections 3 & 6 to the mounting foot or alternatively this is replaced by a link which directly earths the foot and these components are mounted on the base printed circuit board. The 'module base' unit offers the option of maintaining the signal connections 2 & 5 and 1 & 4 when the 'module insert' is removed or interrupting these connections.

The 'module insert' comprises an encapsulated printed circuit board (PCB) upon which are mounted the electrical components. The modules use two and three terminal gas discharge tubes, diodes, zener diodes, LED's, resistors and inductors for operational purposes mounted on the module printed circuit board and housed within a plastic module, which when fitted in the 'module base' unit, provides a degree of protection of at least IP20 for the electrical circuit. The 'module insert' is asymmetrical and the PCB edge connector is arranged so that the connections 3 & 6 makes first and breaks last when inserted or removed. Depending on the module two plug in external links may be available to disconnect the signal connections 2 & 5 and 1 & 4.

The SD**Mxxx Series Surge Protection Devices are available in a number of differing configurations and operating voltages. The "*" in the apparatus title indicates the nominal voltage the apparatus is designed to work at. For example a unit marked SD07Mxxx has a nominal working voltage of 7V and an operating voltage of 7.5V. The differing configurations, working voltage and operating voltage of the device are not critical for the safety assessment.

The SD**Mxxx Series Surge Protection Devices may be located in a hazardous area. For all units the permitted input current reduces as the voltage increases and the different input power limit determines the upper limit on the permitted ambient temperature range. The Surge Protected Devices are passive and therefore the surge protected output parameters are equal to the parameters of the device connected to the field terminals.

It is intended that the ‘module base’ and the ‘module insert’ are combined before being supplied for installation and if the ‘module insert’ fails in service it may be easily replaced by an identical unit. However since the differing configurations, working voltage and operating voltage of the assembly are not critical for the safety assessment it is not significant if a different ‘module insert’ is fitted or if the ‘module base’ is installed without a ‘module insert.’

The SD**Mxxx Series Surge Protection Devices are considered to comply with the requirements for intrinsically safe equipment of IEC60079-0:2012+A11:2013 and IEC60079-11:2012 and may be marked with the code:-

All SD**Mxxx Series Surge Protection Devices are marked Ex ia IIC T4 Ga. For the Ambient Temperature limits, see below

Input : Field Terminals

- U_i = 20V I_i = 260mA
- or U_i = 26V I_i = 175mA
- or U_i = 28V I_i = 140mA
- or U_i = 60V I_i = 65mA
- or U_i = 75V I_i = 40mA
- P_i = 1W (-30°C ≤ T_a ≤ 75°C)
- or P_i = 1.2W (-30°C ≤ T_a ≤ 60°C)
- or P_i = 1.3W (-30°C ≤ T_a ≤ 40°C)

C_i = 0 L_i = 0.22mH (All SD**Mxxx units are treated as if L_i = 0.22mH irrespective of if L1 and L2 are fitted.)

Output: Surge Protected Terminals

- U_o ≤ U_i
- I_o ≤ I_i
- P_o ≤ P_i

The surge protected output parameters are equal to the parameters of the device connected to the field terminals.

The safe use of the SD**Mxxx range of Surge Protection Devices is not dependent upon the nominal working voltage, but on the combination of input voltage and current from a certified intrinsically safe source. To accommodate the SD75Mxxx Series Surge Protection Device, the existing input parameters, which are applicable to all SD**Mxxx units within the range, are extended by the addition the higher combination of U_i = 75V and I_i = 40mA. The full Modular Range is shown below.

		Modular Options Only				Model
SD						
	VV					Nominal Working Voltage 07V, 16V, 32V, 55V & 75V
		M				Modular
			F			Fuse
				D		Disconnect Links fitted for maintenance Not now available with “Normally Off with Failure On” option.
					L	LED “Normally Off with Failure On”

Module Insert Options

Working Voltage 7V	Working Voltage 16V	Working Voltage 32V	Working Voltage 55V	Working Voltage 75V	Series Impedance	Disconnect Links	LED
SD07MXX	SD16MXX	SD32MXX	SD55MXX		<0.5Ω		
SD07MXL	SD16MXL	SD32MXL	SD55MXL	SD75MXL	<0.5Ω		Fitted
SD07MDX	SD16MDX	SD32MDX	SD55MDX		2-2.4 Ω	Fitted	
SD07MFX	SD16MFX	SD32MFX	SD55MFX		2-2.4 Ω	Disconnect Fuse Fitted	

Module Base Options

'Module Base' Type	Gas discharge tube connects 3 & 6 to the mounting foot	Maintains the signal connections 2 & 5 and 1 & 4 with 'module insert' removed
SDBE-BCN	Not fitted	Maintains the signal connections, with insert removed
SDBE-BDN	Not fitted	Disconnects signal connections, with insert removed
SDBE-BCG	Fitted	Maintains the signal connections, with insert removed
SDBE-BDG	Fitted	Disconnects signal connections, with insert removed