



IECEX Certificate of Conformity

INTERNATIONAL ELECTROTECHNICAL COMMISSION IEC Certification Scheme for Explosive Atmospheres

for rules and details of the IECEx Scheme visit www.iecex.com

Certificate No.: IECEx BAS 07.0068 issue No.:8

Status: **Current**

Date of Issue: 2017-03-27 Page 1 of 4

Applicant: **Eaton Electric Limited**
Great Marlings
Butterfield
Luton
Bedfordshire
LU2 8DL
United Kingdom

Certificate history:
Issue No. 8 (2017-3-27)
Issue No. 7 (2016-10-5)
Issue No. 6 (2014-3-5)
Issue No. 5 (2011-12-6)
Issue No. 4 (2011-1-31)
Issue No. 3 (2010-8-17)
Issue No. 2 (2010-3-11)
Issue No. 1 (2009-5-6)
Issue No. 0 (2007-11-12)

Equipment: **MTL552* Series Solenoid / Alarm Drivers**
Optional accessory:

Type of Protection: **Intrinsic Safety**

Marking: **[Ex ia Ga] IIB (Model 5522 only)**
[Ex ia Ga] IIC
[Ex ia Da] IIIC
[Ex ia Ma] I
-20°C ≤ Ta ≤ +60°C - All models except MTL5521-T
-20°C ≤ Ta ≤ +65°C - MTL5521-T Model only

Approved for issue on behalf of the IECEx Certification Body: R S Sinclair

Position: Technical Manager

Signature:
(for printed version)

Date:

27 MARCH 2017

1. This certificate and schedule may only be reproduced in full.
2. This certificate is not transferable and remains the property of the issuing body.
3. The Status and authenticity of this certificate may be verified by visiting the [Official IECEx Website](http://www.iecex.com).

Certificate issued by:

SGS Baseefa Limited
Rockhead Business Park
Staden Lane
Buxton, Derbyshire, SK17 9RZ
United Kingdom





IECEX Certificate of Conformity

Certificate No.: IECEx BAS 07.0068

Date of Issue: 2017-03-27

Issue No.: 8

Page 2 of 4

Manufacturer: **Eaton Electric Limited**
Great Marlings
Butterfield
Luton
Bedfordshire
LU2 8DL
United Kingdom

Additional Manufacturing location(s):

**MTL Instruments PVT
Limited**
No 3 Old Mahabalipuram
Road
Sholinganallur
Chennai
India

This certificate is issued as verification that a sample(s), representative of production, was assessed and tested and found to comply with the IEC Standard list below and that the manufacturer's quality system, relating to the Ex products covered by this certificate, was assessed and found to comply with the IECEx Quality system requirements. This certificate is granted subject to the conditions as set out in IECEx Scheme Rules, IECEx 02 and Operational Documents as amended.

STANDARDS:

The electrical apparatus and any acceptable variations to it specified in the schedule of this certificate and the identified documents, was found to comply with the following standards:

IEC 60079-0 : 2011 Explosive atmospheres - Part 0: General requirements
Edition: 6.0

IEC 60079-11 : 2011 Explosive atmospheres - Part 11: Equipment protection by intrinsic safety "i"
Edition: 6.0

*This Certificate **does not** indicate compliance with electrical safety and performance requirements other than those expressly included in the Standards listed above.*

TEST & ASSESSMENT REPORTS:

A sample(s) of the equipment listed has successfully met the examination and test requirements as recorded in

Test Report:

GB/BAS/ExTR07.0128/00
GB/BAS/ExTR10.0298/00
GB/BAS/ExTR16.0238/00

GB/BAS/ExTR10.0025/00
GB/BAS/ExTR11.0302/00
GB/BAS/ExTR17.0097/00

GB/BAS/ExTR10.0197/00
GB/BAS/ExTR14.0043/00

Quality Assessment Report:

GB/BAS/QAR06.0022/06

GB/BAS/QAR07.0017/06



IECEX Certificate of Conformity

Certificate No.: IECEx BAS 07.0068

Date of Issue: 2017-03-27

Issue No.: 8

Page 3 of 4

Schedule

EQUIPMENT:

Equipment and systems covered by this certificate are as follows:

The MTL552* Series Solenoid / Alarm Drivers are designed to control and monitor a device located in the hazardous area and restrict the transfer of energy from unspecified apparatus in the non-hazardous area to an intrinsically safe circuit in the hazardous area by the limitation of voltage and current. A transformer and opto-isolators provide galvanic isolation between the hazardous and non-hazardous area circuitry.

The apparatus comprises an isolating transformer, opto-isolators, duplicated zener diode chains and current limiting resistors to provide voltage and current limitation. The above, together with other electronic components are mounted on a printed circuit board (PCB) and housed in a moulded plastic enclosure. Polarised plugs and sockets are provided for hazardous and non-hazardous area connections.

The MTL552* Series Solenoid / Alarm Drivers comprise a number of different models denoted by * in the model number. All models are built on a common PCB and are configured have certain features such as Line Fault Detection (LFD) and Phase Reversal facilities. There are also models in the range that are loop powered or have low current hazardous area outputs. All models have LED indication dependent on the model configuration.

With exception of the MTL5521-T Loop Powered Solenoid / Alarm Driver, all MTL552* models have an ambient temperature range of -20°C to +60°C. The MTL5521-T variant has an extended ambient temperature range of -20°C to +65°C.

See annex for model information and electrical data.

SPECIFIC CONDITIONS OF USE: NO



IECEX Certificate of Conformity

Certificate No.: IECEx BAS 07.0068

Date of Issue: 2017-03-27

Issue No.: 8

Page 4 of 4

DETAILS OF CERTIFICATE CHANGES (for issues 1 and above):

Variation 8.1

To permit the addition of the MTL5521-T Loop Powered Solenoid / Alarm Driver to the range covered by the certificate. The MTL5521-T is of similar construction to the MTL5521 variant and has the same input and output parameters, but has an extended ambient temperature range of -20°C to +65°C.

The Equipment Marking section and Schedule was revised to detail the new variant of the equipment. The Certificate Annex (now Issue 5) was updated to list the new variant.

ExTR: GB/BAS/ExTR17.0097/00

File Reference: 17/0166

MTL552* Series Solenoid / Alarm Drivers

Model Range

Model No.	
MTL5521	Loop Powered Solenoid / Alarm Driver
MTL5521-T	Loop Powered Solenoid / Alarm Driver
MTL5522	Loop Powered Solenoid / Alarm Driver, IIB
MTL5523	Solenoid / Alarm Driver with Line Fault Detection Alarm
MTL5523V	Solenoid / Alarm Driver with Line Fault Detection Alarm
MTL5523VL	Solenoid / Alarm Driver with Line Fault Detection Alarm
MTL5524	Solenoid / Alarm Driver with Logic Control, Phase Reversal
MTL5525	Low Current Solenoid / Alarm Driver

MTL5521, MTL5521-T, MTL5523, MTL5523V & MTL5524 Model Parameters

Non-Hazardous Area Terminals 7 to 14

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 / 3 w.r.t. 1

$$\begin{aligned}
 U_o &= 25V & C_i &= 0 \\
 I_o &= 147mA & L_i &= 0 \\
 P_o &= 0.92W
 \end{aligned}$$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

GROUP	CAPACITANCE (μ F)	INDUCTANCE (mH)	OR	L/R RATIO (μ H/ohm)
IIC	0.11	1.4		40
IIB**	0.84	7.2		159
IIA	2.97	14.4		328
I	4.87	20.2		478

** Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
 - the total L_i of the external circuit (excluding the cable) is < 1% of the L_o value or
 - the total C_i of the external circuit (excluding the cable) is < 1% of the C_o value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
 - the total L_i of the external circuit (excluding the cable) is \geq 1% of the L_o value and
 - the total C_i of the external circuit (excluding the cable) is \geq 1% of the C_o value.

The reduced capacitance of the external circuit (including cable) shall not be greater than 1 μ F for Groups IIB, IIA & I and 600nF for Group IIC.

MTL5522 Model Parameters

Non-Hazardous Area Terminals 7 to 14

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 / 3 w.r.t. 1

$$\begin{aligned} U_o &= 25V & C_i &= 0 \\ I_o &= 166mA & L_i &= 0 \\ P_o &= 1.04W \end{aligned}$$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

GROUP	CAPACITANCE (μF)	INDUCTANCE (mH)	OR	L/R RATIO ($\mu H/ohm$)
IIB*	0.84	5.6		132
IIA	2.97	10.4		286
I	4.87	16.0		428

*Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
 - the total L_i of the external circuit (excluding the cable) is $< 1\%$ of the L_o value or
 - the total C_i of the external circuit (excluding the cable) is $< 1\%$ of the C_o value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
 - the total L_i of the external circuit (excluding the cable) is $\geq 1\%$ of the L_o value and
 - the total C_i of the external circuit (excluding the cable) is $\geq 1\%$ of the C_o value.

The reduced capacitance of the external circuit (including cable) shall not be greater than $1\mu F$ for Groups IIB, IIA & I and $600nF$ for Group IIC.

MTL5523VL Model Parameters

Non-Hazardous Area Terminals 7 to 14

$$U_m = 253V$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 / 3 w.r.t. 1

$$\begin{aligned} U_o &= 25V \\ I_o &= 108mA \\ P_o &= 0.68W \\ C_i &= 0 \\ L_i &= 0 \end{aligned}$$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

GROUP	CAPACITANCE (μF)	INDUCTANCE (mH)	OR	L/R RATIO ($\mu\text{H}/\text{ohm}$)
IIC	0.11	3.04		52
IIB*	0.84	12.19		210
IIA	2.97	24.38		421
I	4.28	40.0		691

*Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
 - the total L_i of the external circuit (excluding the cable) is $< 1\%$ of the L_o value or
 - the total C_i of the external circuit (excluding the cable) is $< 1\%$ of the C_o value.
- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
 - the total L_i of the external circuit (excluding the cable) is $\geq 1\%$ of the L_o value and
 - the total C_i of the external circuit (excluding the cable) is $\geq 1\%$ of the C_o value.

The reduced capacitance of the external circuit (including cable) shall not be greater than $1\mu\text{F}$ for Groups IIB, IIA & I and 600nF for Group IIC.

MTL5525 Model Parameters

Non-Hazardous Area Terminals 7 to 14

$$U_m = 253\text{V}$$

The apparatus is designed to operate on the above terminals from a d.c. supply voltage of up to 35V.

Hazardous Area Terminals 2 / 3 w.r.t. 1

$$\begin{aligned} U_o &= 25\text{V} & C_i &= 0 \\ I_o &= 83.3\text{mA} & L_i &= 0 \\ P_o &= 0.52\text{W} \end{aligned}$$

The capacitance and either the inductance or the inductance to resistance ratio (L/R) of the hazardous area load connected must not exceed the following values:

GROUP	CAPACITANCE (μF)	INDUCTANCE (mH)	OR	L/R RATIO ($\mu\text{H}/\text{ohm}$)
IIC	0.11	5.3		68
IIB	0.84	21.8		254
IIA	2.97	44.7		536
I	4.87	64.9		814

*Group IIB parameters also applicable for associated apparatus [Ex ia Da] IIIC

Notes:

- 1) The above load parameters apply when one of the two conditions below is given:
 - the total L_i of the external circuit (excluding the cable) is $< 1\%$ of the L_o value or
 - the total C_i of the external circuit (excluding the cable) is $< 1\%$ of the C_o value.

- 2) The above parameters are reduced to 50% when both of the two conditions below are given:
 - the total L_i of the external circuit (excluding the cable) is $\geq 1\%$ of the L_o value and
 - the total C_i of the external circuit (excluding the cable) is $\geq 1\%$ of the C_o value.

The reduced capacitance of the external circuit (including cable) shall not be greater than $1\mu\text{F}$ for Groups IIB, IIA & I and 600nF for Group IIC.